



# Kurio Touch 4S Battery Replacement

The battery can be removed and replaced if damaged.

Written By: Khalid AlTamimi



## INTRODUCTION

This guide will show you how to replace your Kurio's battery.

---

### TOOLS:

- [iFixit Opening Tools](#) (1)
  - [Phillips #1 Screwdriver](#) (1)
  - [Soldering Station](#) (1)
-

## Step 1 — Battery



- Make sure to open the back cover easily using the plastic opening tool.

## Step 2



- Remove back cover by prying away from the device.
- The easiest place to remove the cover is from the bottom and top, then try to open it from the right and left sides.

⚠ Open it gently. Do not open it with too much pressure, so that the plastic back cover do not break.



## Step 3




- To remove the battery, make sure the four 5mm Philips screws on each side of your device is open using the Phillips #1 Screwdriver.

## Step 4



- After you remove your four screws use your plastic opening tool to help you open the plastic cover of your device.

## Step 5



- Use the plastic opening tool to remove the battery from its place.
- ⚠ The battery is glued into the device. So try removing it gently.

## Step 6



- Remove the two wires using soldering tool to detach your bad battery from the device .
- ⚠ Gently remove the wires one by one. Do not damage the head that is glued into the motherboard.
- ⓘ For more information on how to solder and desolder the wire [Click here](#)

To reassemble your device, follow these instructions in reverse order.